

AC134 Series

Low Frequency Accelerometer, Side Exit 2 Pin Connector, 500 mV/g, ±10%



VIBRATION ANALYSIS HARDWARE



Product Features

Designed for Low-Speed Rotors, Main Bearings, and Gear Box Inputs, but Can Also be Used for High Frequency Detection

May be Used With Any Application That Requires Low and High Frequency Measurements

- ▶ 500 mV/g Sensitivity, ±10% Sensitivity
- ▶ 0.1 Hz for Low-Frequency Measurements
8,000 Hz for High-Frequency Detection
- ▶ Standard 2 Pin MIL Connection or Integral Cable

Note: Integral Cable Options are Only for Permanent Monitoring Applications

AC134-1D 2 Pin Connector	AC134-2D CB103 Integral Cable	AC134-3D CB206 Armored Integral Cable	AC134-6D CB611 Heavy Duty Armored Integral Cable																														
<table border="1"> <thead> <tr> <th>Connector Pin</th> <th>Polarity</th> </tr> </thead> <tbody> <tr> <td>A</td> <td>(+) Signal/Power</td> </tr> <tr> <td>B</td> <td>(-) Common</td> </tr> </tbody> </table>	Connector Pin	Polarity	A	(+) Signal/Power	B	(-) Common	<table border="1"> <thead> <tr> <th>Conductor</th> <th>Polarity</th> </tr> </thead> <tbody> <tr> <td>Red</td> <td>(+) Signal/Power</td> </tr> <tr> <td>Black</td> <td>(-) Common</td> </tr> <tr> <td>Shield</td> <td>Cable Drain Wire</td> </tr> </tbody> </table>	Conductor	Polarity	Red	(+) Signal/Power	Black	(-) Common	Shield	Cable Drain Wire	<table border="1"> <thead> <tr> <th>Conductor</th> <th>Polarity</th> </tr> </thead> <tbody> <tr> <td>Red</td> <td>(+) Signal/Power</td> </tr> <tr> <td>Black</td> <td>(-) Common</td> </tr> <tr> <td>Shield</td> <td>Cable Drain Wire</td> </tr> </tbody> </table>	Conductor	Polarity	Red	(+) Signal/Power	Black	(-) Common	Shield	Cable Drain Wire	<table border="1"> <thead> <tr> <th>Conductor</th> <th>Polarity</th> </tr> </thead> <tbody> <tr> <td>Red</td> <td>(+) Signal/Power</td> </tr> <tr> <td>Black</td> <td>(-) Common</td> </tr> <tr> <td>Shield</td> <td>Cable Drain Wire</td> </tr> </tbody> </table>	Conductor	Polarity	Red	(+) Signal/Power	Black	(-) Common	Shield	Cable Drain Wire
Connector Pin	Polarity																																
A	(+) Signal/Power																																
B	(-) Common																																
Conductor	Polarity																																
Red	(+) Signal/Power																																
Black	(-) Common																																
Shield	Cable Drain Wire																																
Conductor	Polarity																																
Red	(+) Signal/Power																																
Black	(-) Common																																
Shield	Cable Drain Wire																																
Conductor	Polarity																																
Red	(+) Signal/Power																																
Black	(-) Common																																
Shield	Cable Drain Wire																																
Built To Order	Built To Order	Built To Order	Built To Order																														

Specifications	Standard	Metric	Specifications	Standard	Metric
Part Number	AC134	M/AC134	Environmental		
Sensitivity (±10%)	500 mV/g		Operating Temperature Range	-58 to 250 °F	-50 to 121 °C
Frequency Response (±3dB)	6-480,000 CPM	0,1-8000 Hz	Maximum Shock Protection	5,000 g, peak	
Frequency Response (±10%)	36-180,000 CPM	0,6-3000 Hz	Electromagnetic Sensitivity	CE	
Dynamic Range	± 16 g, peak *Vsource ≥ 22V, 12Vbias		Sealing	Welded, Hermetic	
Electrical			Submersible Depth	200 ft.	60 m
Settling Time	<2 seconds		SIL Rating	SIL 2	
Voltage Source	18-30 VDC		Physical		
Constant Current Excitation	2-10 mA		Sensing Element	PZT Ceramic	
Spectral Noise @ 10 Hz	1.7 µg/√Hz		Sensing Structure	Shear Mode	
Spectral Noise @ 100 Hz	0.2 µg/√Hz		Weight	5.7 oz	160 grams
Spectral Noise @ 1000 Hz	0.12 µg/√Hz		Case Material	316L Stainless Steel	
Output Impedance	<100 ohm		Connector (Non-Integral)	2 Pin MIL-C-5015	
Bias Output Voltage	10-14 VDC		Resonant Frequency	1,080,000 CPM	18000 Hz
Case Isolation	>10 ⁸ ohm		Mounting Torque	2 to 5 ft. lbs.	2,7 to 6,8 Nm
			Mounting Hardware Supplied	1/4-28 Captive Bolt	M6x1 Captive Bolt
			Calibration Certificate	CA10	

Typical Frequency Response

